

PCTWORLD INTELLECTUAL PROPERTY ORGANIZATION
International Bureau

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H03F	A2	(11) International Publication Number: WO 97/06595 (43) International Publication Date: 20 February 1997 (20.02.97)
(21) International Application Number: PCT/IB96/00751 (22) International Filing Date: 26 July 1996 (26.07.96) (30) Priority Data: 9516025.5 4 August 1995 (04.08.95) GB (71) Applicant: PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL). (71) Applicant (for SE only): PHILIPS NORDEN AB [SE/SE]; Kottbygatan 7, Kista, S-164 85 Stockholm (SE). (71) Applicant (for GB only): PHILIPS ELECTRONICS UK LIMITED [GB/GB]; 420-430 London Road, Croydon CR9 3QR (GB). (72) Inventor: REDMAN-WHITE, William; 5 Goddard Close, West Wellow, Hants S05 6RH (GB). (74) Agent: WHITE, Andrew, Gordon; Internationaal Octrooibureau B.V., P.O Box 220, NL-5600 AE Eindhoven (NL).		(81) Designated States: JP, KR, European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published <i>Without international search report and to be republished upon receipt of that report.</i>
(54) Title: AMPLIFIER (57) Abstract An amplifier, particularly a CMOS amplifier has a differential input (1, 2) which is fed to six differential pairs (P1/P2, P3/P4, P5/P6, N1/N2, N3/N4, N5/N6). The outputs of the first (P1/P2) and third (P5/P6) are combined and fed to inputs (10/11) of a summing network (9), while the outputs of the fourth (N1/N2) and fifth (N3/N4) are combined and fed to inputs (12/13) of the network (9). The second (P3/P4) and sixth (N5/N6) pairs are arranged to cancel the tail currents of the fifth (N5/N6) and third (P5/P6) pairs respectively when all the devices are in their active state. Thus regardless of the common mode input level with respect to the supply rails the output current is provided by four devices giving an constant g_m and slew rate.		

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AM	Armenia	GB	United Kingdom	MW	Malawi
AT	Austria	GE	Georgia	MX	Mexico
AU	Australia	GN	Guinea	NE	Niger
BB	Barbados	GR	Greece	NL	Netherlands
BE	Belgium	HU	Hungary	NO	Norway
BF	Burkina Faso	IE	Ireland	NZ	New Zealand
BG	Bulgaria	IT	Italy	PL	Poland
BJ	Benin	JP	Japan	PT	Portugal
BR	Brazil	KE	Kenya	RO	Romania
BY	Belarus	KG	Kyrgyzstan	RU	Russian Federation
CA	Canada	KP	Democratic People's Republic of Korea	SD	Sudan
CF	Central African Republic			SE	Sweden
CG	Congo	KR	Republic of Korea	SG	Singapore
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LR	Liberia	SZ	Swaziland
CS	Czechoslovakia	LT	Lithuania	TD	Chad
CZ	Czech Republic	LU	Luxembourg	TG	Togo
DE	Germany	LV	Latvia	TJ	Tajikistan
DK	Denmark	MC	Monaco	TT	Trinidad and Tobago
EE	Estonia	MD	Republic of Moldova	UA	Ukraine
ES	Spain	MG	Madagascar	UG	Uganda
FI	Finland	ML	Mali	US	United States of America
FR	France	MN	Mongolia	UZ	Uzbekistan
GA	Gabon	MR	Mauritania	VN	Viet Nam

DESCRIPTION

AMPLIFIER

5 The invention relates to an amplifier and in particular to an input structure therefor comprising first and second differential pairs of opposite conductivity type.

 There is an increasing need for circuit architectures that will yield good analogue performance in circuits operating with low supply voltages and particularly in CMOS circuits. Modern sub-micron processes stipulate 3.3 volts
10 as the nominal supply voltage. For most amplifier structures this poses a problem. Conventional differential pair inputs can only operate with a common mode offset from one of the power supply rail voltages sufficient to allow the amplifying transistors and the tail current source to be in an active state. This
15 implies for MOS transistors a minimum of $V_T + 2 V_{dsat}$ from one rail (V_{dd} for a P-channel input or V_{ss} for an N-channel input). This is a severe limitation on systems design where signal voltages should ideally be kept large to maintain a good signal to noise ratio.

 One proposed solution is to use two differential pairs, one P-channel and
20 one N-channel and to connect them in parallel in a signal sense. To achieve this the gates of the two differential pairs are simply connected to the inputs and a folded cascode or similar structure is used to sum the resulting output currents. Hence, when the common mode input signal value is low, the N-channel pair will be turned off but a signal will be present due to the P-channel
25 pair. When the input common mode value is near V_{dd} the converse situation applies. When the input is near to $V_{dd}/2$ both differential pairs are delivering signal current to the summing circuit. Such an arrangement is described in a paper entitled "A compact power efficient 3V CMOS rail-to-rail input/output operational amplifier for VLSI cell libraries" by R. Hogervorst, J. R. Tero, R. G.
30 H. Eschauzier and J H Huijsing, published in IEEE Journal of Solid State Circuits, Vol. 29, No. 12, December 1994.

There are two drawbacks to the basic idea. First it can be seen that the effective small signal transconductance of the stage varies with common mode value of the incoming signal. At each extreme the transconductance is one half of that in the mid range. This is due to there being only one pair of devices active in the regions near each supply rail. This has an impact on the usability of the circuit since when used as a transconductor the proportionality is varying with signal value and when used as an operational amplifier there is now the problem that the compensation system for closed loop stability will not be well defined and the phase margin will be signal level dependent.

The second problem concerns the large signal behaviour. With a large differential input signal there is normally a well defined maximum current from a normal differential pair which sets the slew rate in amplifiers and the response time in comparators, where a transconductor is often used to drive a single ended current integrator (typically just a CMOS inverter). The simple dual differential pair has a maximum slew rate of I , where I is the tail current of each of the differential pairs, when the common mode input is near each power rail since the opposing tail current source will be turned off. In the mid range when both differential pairs are active the maximum slew rate current is $2I$.

The arrangement proposed by Hogervorst et. al. in the paper referenced above attains a relatively constant g_m in the following manner. Because for moderate biases the g_m of a MOS transistor is proportional to the square root of its drain current, the loss of the total g_m when only one pair is active may be compensated by increasing the current in the active pair by the ratio of 4:1, hence doubling its g_m . This is achieved by means of two control loops which sense the current in each pair. The switch-off point for each differential pair is detected by a current steering circuit, and the unused tail current is sent to a multiplying mirror. This then feeds an additional current of $3I$ to the opposing active pair.

This gives a good control of the transconductance but two problems still remain. First the total current available for slewing is still not constant and will

increase by a factor of two when the input common mode signal is near the power supply rails. Secondly, the control system requires current to flow through a circuitous loop with current mirrors of inherently limited bandwidth which will limit the frequency of common mode signal that can be handled.

5 It is an object of the invention to enable the production of an amplifier arrangement which may be used with low supply voltages in which the effect of one or more of the disadvantages set out above may be mitigated.

The invention provides an amplifier comprising differential input means, a plurality of differential pairs of active devices of a first conductivity type, a
10 plurality of differential pairs of active devices of a second conductivity type, means for connecting the differential input means to the inputs of the differential pairs, and means for combining the outputs of the differential pairs, wherein for all values of input signal the same total tail current flows through the same total differential pair device sizes allowing for scaling
15 between devices of the first and second conductivity types.

By ensuring that the same total tail current flows through the same effective differential pair sizes a substantially constant g_m and slew rate can be achieved over the whole input signal voltage range. It will be apparent to the person skilled in the art that when using MOS transistors as the active devices
20 the p and n channel devices have to be scaled to obtain the same device parameters, i.e. the actual sizes are different but the transconductances are equal.

The invention further provides an amplifier comprising first, second, and third differential pairs of active devices of a first conductivity type having first, second, and third tail currents respectively, fourth, fifth, and sixth differential
25 pairs of active devices of a second conductivity type having fourth, fifth, and sixth tail currents respectively: wherein each of said differential pairs has its inputs coupled to the inputs of the amplifier, the outputs of the first, third, fourth, and fifth differential pairs are coupled to inputs of a summing network whose output is coupled to the output of the amplifier, the outputs of the
30 second differential pair are commoned and connected to the tail of the fifth

differential pair, the outputs of the sixth differential pair are commoned and connected to the tail of the third differential pair, the tail current of the second differential pair is equal to that of the fifth differential pair, and the tail current of the third differential pair is equal to that of the sixth differential pair.

5 The action of the first, third, fourth, and sixth differential pairs ensures that the large signal output current and the total transconductance is held substantially constant regardless of whether devices of both the conductivity types are active or whether devices of one of the conductivity types are cut off. This is achieved without the use of current mirrors and is achieved by means
10 of a feed forward technique, thus reducing stability and bandwidth problems.

 In one implementation the active devices are p-channel and n-channel MOS transistors. The amplifier may be such that all the p-channel transistors are identical, all the n-channel devices are identical, and the devices are constructed so that the p-channel devices have the same nominal
15 transconductance as the n-channel devices, the tail current of the third differential pair being equal to the tail current of the sixth differential pair and the tail current of the fifth differential pair being equal to the tail current of the second differential pair.

 Such an arrangement provides a convenient design enabling a well
20 defined change in the active devices which contribute to the output current with changing common mode input voltage. It is possible to make the tail currents or transconductances of the transistor pairs non-equal depending on the total characteristics required. In this way the amplifier transconductance or slew rate characteristics can be optimised for a given application.

25 The above and other features and advantages of the invention will become apparent from the following description, by way of example, of an embodiment of the invention with reference to the accompanying drawing which shows a circuit diagram of an amplifier according to the invention.

 As shown in the Figure the amplifier comprises three differential pairs
30 of p-channel field effect transistors P1 to P6 and three differential pairs of n-channel transistors N1 to N6. A first input 1 is connected to the gate electrodes

of transistors P1, P3, P5, N1, N3 and N5, while a second input 2 is connected to the gate electrodes of transistors P2, P4 and P6 and N2, N4 and N6. The source electrodes of transistors P1 and P2 are connected via a current source 3 to a supply rail V_{dd} , while the source electrodes of transistors P3 and P4 are connected through a current source 4 to the supply rail V_{dd} , and the source electrodes of transistor P5 and P6 are connected through a current source 5 to the supply rail V_{dd} . Similarly the source electrodes of transistors N1 and N2 are connected to a supply rail V_{ss} via a current source 6, the source electrodes of transistors N3 and N4 are connected to the supply rail V_{ss} via a current source 7, and the source electrodes of transistors N5 and N6 are connected to the supply rail V_{ss} through a current source 8. The drain electrodes of transistors P3 and P4 are connected to the junction of the source electrodes of transistors N3 and N4, while the drain electrodes of transistors N5 and N6 are connected to the junction of the source electrodes of transistors P5 and P6. A summing network 9 has four inputs 10, 11, 12 and 13. The drain electrodes of transistors P2 and P6 are connected to the input 10, the drain electrodes of transistors P1 and P5 are connected to the input 11, The drain electrodes of transistors N1 and N3 are connected to the input 12, and the drain electrodes of transistors N2 and N4 are connected to input 13. The output of the summing network 9 is connected to an output 14 of the amplifier. The current sources 3 to 8 each pass the current I .

All the n-channel transistors are of equal size as are all the p-channel transistors. The width and length of the n and p-channel devices are scaled to obtain the same g_m at the same current.

In the middle region of the common mode input where both the n and p-channel devices contribute to the output, the output of transistors N1 and N2 are summed in the summing network 9 with the output of transistors P1 and P2. The tail current of transistors N3 and N4, which are connected in parallel with transistors N1 and N2, is sourced from the transistors P3 and P4. Thus transistors N3 and N4 will not contribute to the output since there is no tail current passing through them. Similarly in parallel with the transistors P1 and

P2 are transistors P5 and P6. However, the tail current from transistors P5 and P6 is conducted by the transistors N5 and N6 turning off the transistors P5 and P6. Consequently only transistors P1, P2, N1 and N2 contribute to the outputs with tail currents I in each pair and the total tail current summed is $2 \times I$.

5 If now the input common mode level is close to the V_{dd} transistors P1, P2, P3 and P4 will be turned off as well as transistors P5 and P6. As a result the tail current sources associated with transistors P1, P2, P3 and P4 will collapse and so there will be no diversion of the tail current from transistors N3 and N4 and these will now contribute to the output. The current source
10 associated with transistors P5 and P6 is not off and still sources the current through transistors N5 and N6. The total output is thus due to transistors N1 and N2, and N3 and N4 each pair operating with a tail current I .

Finally the situation where the common mode input signal is near to V_{ss} transistors N1 to N6 will now be off and the current sources feeding transistors
15 N1, N2, N5, and N6 will collapse. Hence there is no diversion of current away from transistors P5 and P6 which will now contribute to the output. The current source associated with transistors N3 and N4 remains active so the total output is due to transistor pairs P1 and P2 and P5 and P6, each operating with the tail current I .

20 Thus, to summarise when the input voltage is close to the supply rail V_{dd} two transistor pairs, that is transistors N1 and N2, and N3 and N4 produce the output, each pair having a tail current I . When the input signal is near to the supply rail V_{ss} two transistor pairs P1 and P2, and P5 and P6 contribute to the output each pair having the tail current I . When the input signal is intermediate
25 the two supply rails V_{dd} and V_{ss} two pairs again contribute to the output this time being transistors N1 and N2 and transistors P1 and P2. Thus at all times the same number of transistors each having the same nominal transconductance and bearing the same tail currents contribute to the output. As a result the amplifier has a substantially constant g_m and slew rate.

30 The summing network can be of any convenient form. An appropriate network is a composite folding and current mirror arrangement as shown in the

paper by Hogervorst et. al. referred to in the introduction.

The current sources 6 and 7 may be combined into a single current source having a current $2I$. Similarly the current sources 3 and 5 may be combined into a single current source. This is particularly so when MOS field effect transistors are used as the amplifying devices as shown in this embodiment. It is not essential that all the current sources 3 to 8 pass the same current I . One possibility would be for sources 3, 4, and 5 to pass the current $2I$ and sources 1, 2, and 6 to pass the current I . In that case the total tail current contributing to the output would remain at $3I$.

Although the embodiment described uses P-channel and N-channel MOS field effect transistors any pairs of complimentary active devices could be used. For example MESFETs or Bipolar transistors. In the latter case it would be preferable to use the separate current sources as shown in the embodiment to avoid current hogging when the current source transistors are pushed into saturation.

From reading the present disclosure, other modifications will be apparent to persons skilled in the art. Such modifications may involve other features which are already known in the design and use of electrical or electronic circuits and component parts thereof and which may be used instead of or in addition to features already described herein. Although claims have been formulated in this application to particular combinations of features, it should be understood that the scope of the disclosure of the present application also includes any novel feature or any novel combination of features disclosed herein either explicitly or implicitly or any generalisation of one or more of those features which would be obvious to persons skilled in the art, whether or not it relates to the same invention as presently claimed in any claim and whether or not it mitigates any or all of the same technical problems as does the present invention. The applicants hereby give notice that new claims may be formulated to such features and/or combinations of such features during the prosecution of the present application or of any further application derived

therefrom.

CLAIMS

1. An amplifier comprising differential input means, a plurality of differential pairs of active devices of a first conductivity type, a plurality of
5 differential pairs of active devices a second conductivity type, means for connecting the differential input means to the inputs of the differential pairs, and means for combining the output of the differential pairs; wherein for all values of input signal the same total tail current flows through the same total differential pair device sizes allowing for scaling between devices of the first
10 and second conductivity types.

2. A differential amplifier comprising differential inport means, first, second, and third differential pairs of active devices of a first conductivity type having first, second, and third tail currents respectively, fourth, fifth, and sixth
15 differential pairs of active devices of a second conductivity type having fourth, fifth, and sixth tail currents respectively; wherein each of said differential pairs has its inputs coupled to the inputs of the amplifier, the outputs of the first, third, fourth, and fifth differential pairs are coupled to inputs of a summing network whose output is coupled to the output of the amplifier, the outputs of
20 the second differential pair are commoned and connected to the tail of the fifth differential pair, the outputs of the sixth differential pair are commoned and connected to the tail of the third differential pair, the tail current of the second differential pair is equal to that of the fifth differential pair, and the tail current of the third differential pair is equal to that of the sixth differential pair.

25

3. A differential amplifier as claimed in Claim 2 in which all the tail currents are equal, all the devices of the first conductivity type are identical, all the devices of the second conductivity type are equal, and the transconductances of the devices of the first conductivity type are equal to the
30 transconductances of the devices of the second conductivity type.

4. An amplifier as claimed in any preceding claim in which the active devices of the first conductivity type are p-channel MOS transistors and the active devices of the second conductivity type are n-channel MOS transistors.

5

5. An amplifier as claimed in Claim 4 in which all the p-channel transistors are identical, all the n-channel transistors are identical, and the devices are constructed so that the p-channel devices have the same nominal transconductance as the n-channel devices, the tail current of the third differential pairs being equal to half the combined tail current of the first and fifth differential pairs and the tail current of the fourth differential pair being equal to half the combined tail current of the second and sixth differential pairs.

10

6. A differential amplifier as claimed in Claim 1 comprising first, second, and third differential pairs of active devices of a first conductivity type having first, second, and third tail currents respectively, fourth, fifth, and sixth differential pairs of active devices of a second conductivity type having fourth, fifth, and sixth tail currents respectively: wherein each of said differential pairs has its inputs coupled to the inputs of the amplifier, the outputs of the first, third, fourth, and fifth differential pairs are coupled to inputs of a summing network whose output is coupled to the output of the amplifier, the outputs of the second differential pair are commoned and connected to the tail of the fifth differential pair, the outputs of the sixth differential pair are commoned and connected to the tail of the third differential pair, the tail current of the second differential pair is equal to that of the fifth differential pair, and the tail current of the third differential pair is equal to that of the sixth differential pair.

15

20

25

7. An amplifier substantially as described herein with reference to the accompanying drawings.

30

8. Any novel feature as novel combination of features disclosed

herein either explicitly or implicitly whether or not it relates to the same invention as that claimed in any preceding claim.

1/1

